

Vanderbilt SC7 Smart Card Reader

Overview

The Vanderbilt SC7 smart card reader was tested on a Net2 Plus control unit with Net2 v6.05. To configure the reader, set the following in the door reader settings:


- Token type set to 'Token Only'
- Reader type set to 'Wiegand Reader'
- Token data format set to 'Wiegand custom'

In the Net2 Server Configuration Utility, set the wiegand rule to:
AAAAAAAAAAAAAAAAAAAAAAAAAAAA

Wiegand reader / Wiegand custom card formats can be used.



Cable Pinout	ACU terminal
Red 7-15DC	+12V
-	Red LED
-	Amber LED
-	Green LED
Green	Wiegand D0
White	Wiegand D1
-	NOT USED
Black	0V



Ensure any unused wires are safely terminated.

The reader's green LED flashes when access is granted.

For more information visit the manufacturers website:

https://www.smarthof.ru/upload/shop_1/2/1/7/item_217542/599ce7a5-a2e3-11e4-9423-bc5ff4125a6c_c80485f8-5696-11e7-8165-ac220b88d047.pdf



+44 (0)1273 811011
support@paxton.co.uk
paxton.support



+49 (0) 251 2080 6900
support@paxton-gmbh.de
paxton.gmbh.support



+33 (0)157 329356
support@paxtonaccess.fr
paxton.support



+32 (0)78485147
support@paxton-benelux.com
paxton.benelux.support



+31 (0)76 3333 999
support@paxton-benelux.com
paxton.benelux.support



+27 (0)21 4276691
support@paxtonaccess.co.za
paxton.support



+1(800) 672-7298
supportUS@paxton-access.com
usapaxton.support



+11 5715088198
soporte@paxton-access.com
paxton.soporte



+1 (864) 751-3501
soporte@paxton-access.com
paxton.soporte



8000 3570 3783
support@paxtonaccess.ae
paxton.support



+44 (0)1273 811011
support@paxton.co.uk
paxton.support