

HID® Signo™ Reader 40

Overview

The Signo™ Reader was wired into a Net2 Plus as below. Configured to use a Wiegand 32 bit rule using all A's, this returned an 8 digit token number in Net2 v6.6.12017.


The token format used was the Mifare Classic 1K.

The response from the reader LED's was, the LED stays green when idle and goes blue/purple - blue/green when a token is presented.

We now have an integration for customers who want to use HID® SEOS tokens whilst still being able to incorporate PaxLocks into the Net2 system. To find out more, head to [APN-1214](#).



Cable Pinout	ACU terminal
RED	+12V
-	Red LED
ORANGE	Amber LED
-	Green LED
GREEN	Wiegand D0
WHITE	Wiegand D1
-	NOT USED
BLACK	0V



Ensure any unused wires are safely terminated.

For more information visit the manufacturers website: <https://www.hidglobal.com/products/40>



+44 (0)1273 811011

support@paxton.co.uk

paxton.support



+49 (0) 251 2080 6900

support@paxton-gmbh.de

paxton.gmbh.support



+33 (0)157 329356

support@paxtonaccess.fr

paxton.support



+32 (0)78485147

support@paxton-benelux.com

paxton.benelux.support



+31 (0)76 3333 999

support@paxton-benelux.com

paxton.benelux.support



+27 (0)21 4276691

support@paxtonaccess.co.za

paxton.support



+1(800) 672-7298

supportUS@paxton-access.com

usapaxton.support



+11 5715088198

soporte@paxton-access.com

paxton.soporte



+1 (864) 751-3501

soporte@paxton-access.com

paxton.soporte



8000 3570 3783

support@paxtonaccess.ae

paxton.support



+44 (0)1273 811011

support@paxton.co.uk

paxton.support