

Connecting a Panasonic BM-ET200 Iris reader to Net2

Overview

The Option Board (BM-ETA201E) will be required for integration with Net2, this board provides the Weigand output.

The software setup of the reader should be carried out by Panasonic technicians. The system users need to be setup on the Panasonic software before integrating with Net2.

Note: This product is now obsolete



Cable Pinout		ACU terminal
-	-	+12V
-	-	Red LED
-	-	Amber LED
-	-	Green LED
9	Access control panel - Data 0	Wiegand D0
10	Access control panel - Data 1	Wiegand D1
-	-	NOT USED
8	Access control panel - Gnd	0V

1	Red 12V dc
2	Red LED
3	Amber LED
4	Green LED
5	Data/D0
6	Clock/D1
7	Media Detect
8	0V out

Ensure any unused wires are safely terminated.

● Setup Switches of Interface Board SW1

For access control panel	
Wiegand	SW1 SW2
	SW1 SW2
	1 2 3 4 1 2 3 4

SW1 OFF SW2 1&2 ON
3&4 OFF



+44 (0)1273 811011
support@paxton.co.uk
paxton.support



+49 (0) 251 2080 6900
support@paxton-gmbh.de
paxton.gmbh.support



+33 (0)157 329356
support@paxtonaccess.fr
paxton.support



+32 (0)78485147
support@paxton-benelux.com
paxton.benelux.support



+31 (0)76 3333 999
support@paxton-benelux.com
paxton.benelux.support



+27 (0)21 4276691
support@paxtonaccess.co.za
paxton.support



+1(800) 672-7298
supportUS@paxton-access.com
usapaxton.support



+11 5715088198
soporte@paxton-access.com
paxton.soporte



+1 (864) 751-3501
soporte@paxton-access.com
paxton.soporte



8000 3570 3783
support@paxtonaccess.ae
paxton.support



+44 (0)1273 811011
support@paxton.co.uk
paxton.support