


Connecting a TagMaster XT-1 to Net2

Overview

The tested XT-1 was configured with the following DIP switch settings:

- S101 positions 6-8: ON-OFF-ON (8-digit Magstripe)




- S301 positions 6-8: OFF-OFF-OFF (pull-ups disabled)



The TagMaster reader is recommended to be used with 24VDC, 0.5A supply. The reader cannot be powered from Net2 PSU.

Cable Pinout	ACU terminal
IN1+ and IN2+	+12V
IN2-	Red LED
-	Amber LED
IN1-	Green LED
D1/DATA	Data/D0
D0 (CLK)	Clock/D1
CL (LOAD)	NOT USED
GND	0V



Ensure any unused wires are safely terminated.



+44 (0)1273 811011
support@paxton.co.uk
paxton.support



+49 (0) 251 2080 6900
support@paxton-gmbh.de
paxton.gmbh.support



+33 (0)157 329356
support@paxtonaccess.fr
paxton.support



+32 (0)78485147
support@paxton-benelux.com
paxton.benelux.support



+31 (0)76 3333 999
support@paxton-benelux.com
paxton.benelux.support



+27 (0)21 4276691
support@paxtonaccess.co.za
paxton.support



+1 (800) 672-7298
supportUS@paxton-access.com
usapaxton.support



+11 5715088198
soporte@paxton-access.com
paxton.soporte



+1 (864) 751-3501
soporte@paxton-access.com
paxton.soporte



8000 3570 3783
support@paxtonaccess.ae
paxton.support



+44 (0)1273 811011
support@paxton.co.uk
paxton.support